

Batteries in Sunny Island Systems

List of Approved Batteries



Die Sunny Island product family (SI3.0M, SI4.4M, SI6.0H and SI8.0H) is equipped with an integrated battery management for lead-acid batteries of type FLA and VRLA.

It is also possible to connect an external battery management that uses different battery technologies.

⚠ WARNING

Danger to life due to fire or explosion when batteries are fully discharged

A fire may occur due to incorrect charging of fully discharged batteries. This can result in death or serious injury.

- Before commissioning the system, verify that the battery is not fully discharged.
- Do not commission the system if the battery is fully discharged.
- If the battery is fully discharged, contact the battery manufacturer for further proceedings.
- Only charge fully discharged batteries as instructed by the battery manufacturer.

i Using lead-acid batteries

The battery management integrated in the Sunny Island ensures that the lead-acid battery is charged carefully, deep discharge is avoided and the state of charge of the battery is determined. Prerequisite for optimum operation of the system and, in particular, for gentle treatment of the lead-acid battery is the adjustment of the parameters of the lead-acid battery to the values of each respective application recommended by the battery manufacturer (see operation and installation manual).

i Using lithium-ion and hybrid (sodium)-ion batteries

All lithium-ion and hybrid (sodium)-ion batteries supply a defined nominal current. The full functionality for the PV storage system can only be guaranteed if the battery capacity (battery capacity and battery currents) is matched to the Sunny Island system constellation used. In particular, three-phase systems usually require more than one battery.

- Pay attention to the battery manufacturers' recommendations and minimum configuration lists regarding the suitable dimensioning of the battery (battery type, circuitry and number of battery modules). Only this ensures that the nominal and overload currents specified in the datasheet for the various system constellations and applications can be achieved.

The lithium-ion batteries of the following manufacturers are approved for the SMA Flexible Storage System with the Sunny Island 3.0M / 4.4M / 6.0H / 8.0H:

Manufacturer	Type	Firmware	Self-consumption systems			Battery backup systems			Off-Grid Systems		
			1~	3~	Comment	1~	3~	Comment	1~	3~	Comment
ADS-TEC	StoraXe® Home & Small Business SRS0009		✓	-	-	✓	-	-	-	-	-
Akasol	neoQube		✓	-	-	-	-	-	-	-	-
	neoRack		✓	✓	-	✓	✓	Only for Sunny Island 3.0M and 4.4M	✓	✓	Only for Sunny Island 3.0M and 4.4M
Axitec	AXITEC AXIstorage Li7S	2.04	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
	AXITEC AXIstorage Li9S	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
	AXITEC AXIstorage Li10S	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
BMZ	BMZ ESS 3.0	2.04	✓	✓	-	✓	✓	-	✓	✓	-
	BMZ ESS 7.0	2.04	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
	BMZ ESS 9.0	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
	BMZ ESS X	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
BYD	B-BOX	2.7	✓	✓	-	✓	✓	-	✓	✓	-
	Battery-Box LV	1.0	✓	✓	-	✓	✓	3~ only for Sunny Island 4.4M	-	-	-
	Battery-Box Premium LVL 15.4	BMU: 1.8 BMS: B-1.3	✓	✓	-	✓	✓	-	✓	✓	-
GNB	Sonnenschein lithium	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
Hoppecke	sun powerpack premium	1.1.0 r11767	✓	✓	-	✓	✓	-	✓	✓	-
IBC	SolStore X.X Li	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
Leclanché	Apollion Cube	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator

Manufacturer	Type	Firmware	Self-consumption systems			Battery backup systems			Off-Grid Systems		
			1~	3~	Comment	1~	3~	Comment	1~	3~	Comment
LG Chem	RESU 5.0		✓	-	-	-	-	-	-	-	-
	RESU 6.4 (Plus Extension Pack)		✓	-	Recommended for Sunny Island 3.0M and 4.4M	✓	-	Only for Sunny Island 3.0M and 4.4M	-	-	-
	RESU 3.3		✓	-	Only for Sunny Island 3.0M and 4.4M	-	-	-	-	-	-
	RESU 6.5		✓	-	-	✓	-	Only for Sunny Island 3.0M	-	-	-
	RESU 10		✓	-	-	✓	-	Only for Sunny Island 3.0M and 4.4M	-	-	-
	RESU 13*	1.7.0.3	✓	-	-	✓	-	Only for Sunny Island 4.4M and 6.0H	-	-	-
	RESU Plus Extension Kit		✓	-	Only for Sunny Island 3.0M and 4.4M	✓	-	Only for Sunny Island 3.0M and 4.4M	-	-	-
Mercedes-Benz Energy GmbH	Mercedes-Benz Energiespeicher Home	29.30 - 5.X	✓	-	Recommended for Sunny Island 3.0M and 4.4M	✓	-	Only for Sunny Island 3.0M and 4.4M	-	-	-
	Mercedes-Benz Energy Storage Home (2.0)	10.xx	✓	-	-	-	-	-	-	-	-
Murata	Murata PLC-BMU Solution with IJ1101M		-	-	-	-	-	-	✓	✓	-
Sony	Controller IJ1004C Module FORTELION IJ1001M		✓	✓	-	✓	✓	-	✓	✓	-
SSL Energie GmbH	eSafe©	1.0.35	✓	✓	-	✓	✓	-	✓	✓	-
Tevolt	Tevolt Lithium-Ion storage Li10	3.17	✓	✓	-	✓	✓	-	✓	✓	-
	Tevolt Lithium-Ion storage Li 20 and higher	1.11	✓	✓	-	✓	✓	-	✓	✓	-
	TS-Series	1.06	✓	✓	-	✓	✓	-	✓	✓	-

* RESU13 is designed to be discharged under power of 5 kW in all operating modes (self-consumption system and battery-backup system). The overload capability of the battery is limited to a duration of 3 seconds for all conditions exceeding nominal power. Ensure that the system is operated according to its intended use.

The hybrid (sodium)-ion batteries of the following manufacturers are approved for the SMA Flexible Storage System and the Sunny Island 3.0M / 4.4M / 6.0H / 8.0H:

Manufacturer	Type	Firmware	Self-consumption systems			Battery backup systems			Off-Grid Systems		
			1~	3~	Comment	1~	3~	Comment	1~	3~	Comment
Aquion Energy*	Aspen 48S / 48M		✓	✓	-	✓	✓	-	✓	✓	-

* If services are required, contact Aquion Energy.

The lithium-ion batteries of the following manufacturers are approved for the Sunny Island 4548-US / 6048-US:

Manufacturer	Type	Firmware	Self-consumption systems			Battery backup systems			Off-Grid Systems		
			1~	3~	Comment	1~	3~	Comment	1~	3~	Comment
Axitec	AXITEC AXIstorage Li 7S	2.04	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
	AXITEC AXIstorage Li 9S	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
	AXITEC AXIstorage Li 10S	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
BMZ	BMZ ESS 3.0	2.04	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer
	BMZ ESS 7.0	2.04	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer Emergency power generator
	BMZ ESS 9.0	2.06	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer Emergency power generator
	BMZ ESS X	2.06	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer Emergency power generator
BYD	B-BOX	2.7	✓	✓	-	✓	✓	-	✓	✓	-
Leclanché	Apollion Cube	2.06	✓	✓	-	✓	✓	-	✓	✓	Emergency power generator
Tevolt	Tevolt lithium-ion storage	3.17	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer	✓	✓	Always check UL compatibility with manufacturer
	TS-Series	1.06	✓	✓	-	✓	✓	-	✓	✓	-

The hybrid (sodium)-ion batteries of the following manufacturers are approved for the Sunny Island 4548-US / 6048-US:

Manufacturer	Type	Firmware	Self-consumption systems			Battery backup systems			Off-Grid Systems		
			1~	3~	Comment	1~	3~	Comment	1~	3~	Comment
Aquion Energy*	Aspen 48S / 48M		✓	✓	-	✓	✓	-	✓	✓	-

* If services are required, contact Aquion Energy.